

## ECO<sub>2</sub> 99+ SYNTHETIC MAGNESIA



DESCRIPTION	ECO <sub>2</sub> 99+ synthetic magnesia (MgO) is a <b>fine white powder</b> produced from serpentine tailings using patented ECO <sub>2</sub> technology. <b>Ultrapure MgO content, low bulk density, and totally exempted of Boron.</b> Produced with revolutionary CO <sub>2</sub> captation technology for lowest emissions in the marketplace allowing downstream customers to significantly reduce their carbon footprint.			
USES	ECO <sub>2</sub> 99+ synthetic magnesia matches a wide range of speciality applications within the industrial sector such as HP FM electrical, Mg metal, Mg chemicals, ceramics, cements, pharmaceuticals, UHP MgO, hydrotalcite market, flame retardants, and other ultra high purity applications. It is also suitable to be converted into Mg(OH) <sub>2</sub> .			
CHEMICAL COMPOSITION	Oxide	Unit	ECO <sub>2</sub> 99+ Low React.	ECO₂ 99+ High React.
			Typical (LOI-free)	Typical (LOI-free)
	Magnesium Oxide (MgO)	-	99.74%	99.74%
	Silicon Oxide (SiO <sub>2</sub> )	-	0.07%	0.07%
	Calcium Oxide (CaO)	-	0.03%	0.03%
PHYSICAL PROPERTIES	Property	Unit	Typical	Typical
	Loose Bulk Density	g/cm <sup>3</sup>	0.25	0.25
	Loss On Ignition (LOI)	%	1.5	14.3
	Surface Area (BET)	m²/g	18.5	141.2
	Citric Acid Reactivity	seconds	40	3
CARBON FOOTPRINT	CO <sub>2</sub> emission	t CO <sub>2</sub> e / t MgO	0.26 - 1.26 (ISO 14067:2018 / Cradle-to-gate)	
PACKAGING	$ECO_2$ Magnesia offers a variety of packaging options, including bulk (truck and railcar), bulk bags, and bags. Please contact a sales representative for information.			
STORAGE	Keep away from moisture. Store in a dry place to avoid caking.			

Notice: the information contained herein is, to the best of our knowledge and belief, accurate. Any recommendations or suggestions made are without warranty or guarantee of results since conditions of handling and of use are beyond our control; we therefore, assume no liability for loss or damage incurred by following these suggestions. Seller warrants only that this product will meet the specifications set forth. Any other representation or warranty, either express or implied, is specifically disclaimed including warranties of fitness for a particular purpose and of merchantability. Sellers and manufacturers only obligation shall be to replace such quantity of the product proved to be defective. Before using, user shall determine the suitability of the product for users intended application and user assumes all risk and liability whatsoever in connection therewith. Neither seller nor manufacturer shall be liable in tort, contract or under any theory for any loss or damage, incidental or consequential, arising out of the use of or the inability to use the product.